

Carrier 06F, 06G, And 06L Compressor Nomenclature Chart

	Product Series		Family		Design Variable	Horsepower Per Displacement	CFM		Electrical Characteristics	
Model	0	6	L	H	2	0	9	4	0	0
Digit	1	2	3	4	5	6	7	8	9	10

1st & 2nd Digit
06 Compressor

3 rd Digit – Family		
	Bore	Stroke
F	2 1/2"	2"
G	2 1/2"	2"
L	3 1/4"	2 3/4"

4 th Digit Design Variable	
A	New Manufactured Compressor
H	Remanufactured Compressor

5 th Digit Horsepower per Displacement	
0	Low Horsepower per displacement
1	Medium Horsepower per displacement
2	High Horsepower per displacement

8 th , 9 th , and 10 th Digit Electrical	
100	575 – 3 – 60
300	208/230/460 – 3 – 60
400	208 – 3 – 60
500	230 – 3 – 60
600	400 – 3 – 50
	460 – 3 – 60
800	230 – 3 – 50
	220/440 – 3 – 60
	440/380 – 3 – 60
	550 – 3 – 60

6 th and 7 th Digit CFM		
	G or L	CFM
40	G	39.8
60	G	59.6
09	L	92.4
14	L	138.4
18	L	184.8
28	L	276.8

Family		Old Model #	HP
06G	040	6G40	10
06G	245	6G45	15
06G	060	6G60	15
06G	161	6G63	20
06G	260	6G65	25
06L	009	6L40	25
06L	109	6L43	30
06L	209	6L45	40
06L	014	6L60	40
06L	114	6L63	50
06L	214	6L65	60
06L	018	6L80	50
06L	118	6L83	60
06L	218	6L85	80
06L	028	6L120	80
06L	128	6L123	100
06L	228	6L125	120